L-250BT

Quick Start Guide

OPTICON



- **Trigger key** - press the key to read barcodes
- **Status LED** - shows the operating status
  Barcode:
  - good read: green flash
  - bad read: red flash

  Charging:
  - 500mA USB: orange fade (4 sec cycle)
  - 900mA USB: orange fade (1 sec cycle)
  - Fully charged: green fade (4 sec cycle)

  Low battery:
  - 3 orange flashes
- **Scan window** - ensure it is free from dust and dirt

Test barcodes

Code 128

Code 128

EAN 13

4 070071 967072

Data Matrix

QR Code

Configuration

Quick Start Instructions

OptiConnect

Download OptiConnect at:

https://
opticonnect.
opticon.com

INIT

Bluetooth Mode

HID (Keyboard emulation)

BLE OptiConnect

SPP (Serial emulation)

Bluetooth Connection Setup

Step 1 - Scan Bluetooth mode barcode

that matches the connection method you wish to use. The default mode is HID. The other is OptiConnect mode.

Step 2 - Hold the trigger key for 3 seconds

to make the L-250BT ready to connect or to retry a connection. When the device is connectable, the blue light flashes slowly. When it is connecting, the blue light flashes quickly; you can press the Trigger key again to cancel the connection attempt and return it to discoverable mode. To remove all saved connection information, scan the “INIT” QR code.

Step 3 - To connect your device

in HID mode, use your host device Bluetooth to find and select the L-250BT. The scanner will beep to indicate success or failure. For OptiConnect mode, open OptiConnect, go to ‘Pair Scanner,’ and select the discovered ‘L-250BT’ to connect.

HID (Human Interface Device)

Makes the scanner function like a keyboard, a one-way communication from the L-250BT to your host device.

OptiConnect

This is our free application to manage your scanner and scan data. You can run OptiConnect on Android, iOS, Windows, and Mac.

For information about your L-250BT, including detailed setup instructions, other modes, downloads and more, visit us at:
Opticon: opticon.com/products/l-250BT
Opticon USA: www.opticonusa.com/start/opn

_QSG_L250BT_04-2026